



SYNQ[®]

3 Controller Options with Full Serial Control and Integrated 200W Siren

Fenieux Industries, Inc.
1.800.615.8350

SYNQ-R

Controllers & Sirens



PART #	SYNQ-RS
CONTROLLER	6.8" x 1.6" x 3.5"
RELAY	7.25" x 8.75" x 2.44"
VOLTAGE	12-18VDC
MAX CURRENT	115 Amps
STANDBY CURRENT	0.35 Amps
LOW CURRENT	3 Amps per Output
HIGH CURRENT	10 Amps per Output
INPUTS	16 Positive
OUTPUTS	22 Total Outputs

CERTIFICATIONS:



DESCRIPTION:

The SynQ-R enhances the SynQ platform with a 13-button layout, an integrated slide switch, and a precision rotary knob designed for fast adjustments in the field. Whether changing lighting intensity, scrolling audio functions, or operating custom modes, the rotary control gives operators finer, smoother input than traditional button-only systems. Five backlit color options allow each button to be quickly identified in low-visibility environments, and the system boots in one second for immediate readiness.

- 13 Programmable Buttons
- 5 LED Button Color Options
- Standardized Button Size
- 4 Button Style Configurations: Timer, Toggle, Multi-Press, and Momentary
- 3 Position Slide Switch
- Aluminum Slide Switch Cap
- 6 Position Rotary-Knob
- 8 LED Programmable Traffic Advisor Indicators
- 15+ Programmable Siren Tones
- 20+ Audio Commands
- 200W Dual-Tone Siren
- Horn Ring, Park-Kill, Hands-Free, & Radio Rebroadcast
- PC Programmable
- Firmware Upgradable
- 1 sec. Boot Up Time
- 12 Low Current Positive Outputs
- 6 High Current Positive Outputs
- 4 Low Current Ground Outputs
- 15ft Wire Harness From Controller to Relay
- 15ft PA Mic Cable Length
- Includes SynQ-R Controller, SynQ Relay, & 4x Label Sheets
- Supports Up to 96 Q Serial Lights or 16 Quantum 2.0 Products
- Syncs All Quantum and Q Serial Products



Relay
Military-grade
Aluminum Base



Controller
Polycarbonate
Plastic Base