

## 20X CONTROLLER\*

Controllers & Sirens



<b>PART #</b>	C-4020
<b>CONTROLLER</b>	7.25" x 1.13" x 3.5"
<b>RELAY</b>	6.3" x 4.4" x 1.6"
<b>VOLTAGE</b>	11-16VDC
<b>CURRENT DRAW</b>	100mA @ 13V
<b>AMPS PER OUTPUT</b>	3 Amps @ 13V
<b>EXTERNAL FUSE</b>	125% Circuit Load
<b>INPUTS</b>	2 Ground, 3 Positive
<b>OUTPUTS</b>	20 Outputs @ 60A
<b>WARRANTY</b>	2 Years

### CERTIFICATIONS:



### DESCRIPTION:

Compact, powerful, and purpose-built—the Feniex 20X Controller is the ultimate solution for simple and reliable control in demanding vehicle environments. With no software required, the 20X is engineered for ease of use with direct wiring and an optimized button layout for intuitive operation. Designed with 20 channel outputs, it delivers efficient power distribution in a durable, low-profile housing. Its built-in LED health indicator offers real-time system feedback, while protected terminal sections help prevent accidental shorting during installation or maintenance.

*\*Note: this controller is not programmable.*

- No software required
- 2 Channel Wig Wag
- Solid State Relays
- 2 Low-side Inputs
- 3 High-side Inputs
- Integrated Slide Switch
- Protected Terminal Sections to prevent shorting
- Faceplate available for Troy, Havis, and Jotto
- Compatible with most emergency lights
- Built-in LED Good Health Indicator
- Built-in Day and Night Mode
- Built-in Highbeam Override



Military-grade  
Aluminum Base



Polycarbonate  
Plastic Base