



SYNQ[®]

Feniex Industries, Inc.
1.800.615.8350

3 Controller Options with Full Serial Control and Integrated 200W Siren

SYNQ-H

Controllers & Sirens



PART #	SYNQ-HH
CONTROLLER	3" x 1.25" x 5.25"
RELAY	7.25" x 8.75" x 2.44"
VOLTAGE	12-18VDC
MAX CURRENT	115 Amps
STANDBY CURRENT	0.35 Amps
LOW CURRENT	3 Amps per Output
HIGH CURRENT	10 Amps per Output
INPUTS	16 Positive
OUTPUTS	22 Total Outputs

CERTIFICATIONS:



DESCRIPTION:

The SynQ-H is a compact controller designed for departments and operators who need full system control in a small, easy-to-carry form factor. With 16 programmable buttons and five available backlight colors, the SynQ-H keeps essential functions close at hand without requiring dashboard space. Its ergonomic handheld design and quick one-second boot time make it ideal for confined cabins, tactical units, or mobile users who need reliable access on the move.

- 16 Programmable Buttons
- 5 LED Button Color Options
- Standardized Button Size
- 4 Button Style Configurations: Timer, Toggle, Multi-Press, and Momentary
- 8 LED Programmable Traffic Advisor Indicators
- 15+ Programmable Siren Tones
- 20+ Audio Commands
- 200W Dual-Tone Siren
- Horn Ring, Park-Kill, Hands-Free, & Radio Rebroadcast
- PC Programmable
- Firmware Upgradable
- 1 sec. Boot Up Time
- 12 Low Current Positive Outputs
- 6 High Current Positive Outputs
- 4 Low Current Ground Outputs
- 15ft Wire Harness From Controller to Relay
- Built-In PA Mic
- Includes SynQ-H Controller, SynQ Relay, & 4x Label Sheets
- Supports Up to 96 Q Serial Lights or 16 Quantum 2.0 Products
- Syncs All Quantum and Q Serial Products



Relay
Military-grade
Aluminum Base



Controller
Polycarbonate
Plastic Base