3 Controller Options with Full Serial Control and Integrated 200W Siren



Controllers & Sirens



PART#	SYNQ-SS
CONTROLLER	6.8" x 1.6" x 3.5"
RELAY	7.25" x 8.75" x 2.44"
VOLTAGE	12-18VDC
MAX CURRENT	115 Amps
STANDBY CURRENT	0.35 Amps
LOW CURRENT	3 Amps per Output
HIGH CURRENT	10 Amps per Output
INPUTS	16 Positive
OUTPUTS	22 Total Outputs

## **CERTIFICATIONS:**





## DESCRIPTION:

The SynQ-S is a full-size vehicle controller built for operators who need clear, direct access to their most important functions. Featuring 22 backlit buttons and an integrated slide switch, it provides fast, intuitive control with five selectable button colors for quick mode identification. The system powers on in just one second, giving users instant access to lighting, siren, and auxiliary functions the moment the vehicle is active. A 200W dual-tone siren, 15+ programmable siren tones, and over 20+ audio commands are included through the paired SynQ Relay.

- 22 Programmable Buttons
- 5 LED Button Color Options
- lacktriangle Standardized Button Size
- 4 Button Style Configurations: Timer, Toggle, Multi-Press, and Momentary
- Aluminum Slide Switch Cap
- 3 Position Slide Switch
- 8 LED Programmable Traffic Advisor Indicators
- 15+ Programmable Siren Tones
- 20+ Audio Commands
- 200W Dual-Tone Siren
- Horn Ring, Park-Kill, Hands-Free, & Radio Rebroadcast

- PC Programmable
- Firmware Upgradable
- 1 sec. Boot Up Time
- 12 Low Current Positive Outputs
- 6 High Current Positive Outputs
- 4 Low Current Ground Outputs
- 15ft Wire Harness From Controller to Relay
- 15ft PA Mic Cable Length
- Includes SynQ-S Controller, SynQ Relay, & 4x Label Sheets
- Supports Up to 96 Q Serial Lights or 16 Quantum 2.0 Products
- Syncs All Quantum and Q Serial Products



Relay Military-grade Aluminum Base



Controller Polycarbonate Plastic Base